

## In-Car Video Playback

Press the Play button on the remote. This will bring up the search function. For easier access to your videos from this point, press the up arrow 1 time to highlight the word 'List' and press the enter key. You will now see a list of events that have been recorded with the most recent at the top. Use the up/down arrow keys to move up & down through the list. The right & left keys will turn the page to reveal more events, if there are more than 1 page of events.

During playback, you can FF, FR, pause and slow motion the video. Quickly tapping the 'Pause' key will pause the video; holding it down for a second will stop the video and return to live view.

## CF Card Insert and Removal

To insert or remove a CF card from the recorder, you will need to have the power off. This ensures that all files have been properly closed before removing the card, and allows the boot-up process to properly scan the card on power-on.

**10-8 VIDEO**  
DIGITAL EVIDENCE SOLUTIONS  
www.10-8video.com 888-788-1048



Operator's Manual

**10-8 VIDEO**  
DIGITAL EVIDENCE SOLUTIONS  
www.10-8video.com 888-788-1048

## THANKS!

Thank you for your support of the 10-8 Video Patrol Car Video System! A system designed by a law enforcement officer for his brother officers of smaller departments. After a lot of time in testing and development, I believe that, dollar-for-dollar; feature-for-feature, there is no finer in-car video system on the market.

Now that your system has been installed and is ready for use, there are just a few things I would like to cover regarding the day to day operation of your 10-8 system.

### Enter you unit/car ID:

Using the remote, press the menu key to bring up the main menu. Scroll down to 'System Setup' and press the enter key. Scroll down to DVR ID and enter your unit/call ID. This will be overlaid with the date and time on all video recordings. Repeated use the menu key to back out of the menu system.

### Using the Wireless Microphone.

The wireless microphone provided with your system provides excellent range and clarity, even while inside a building. The belt pack transmitter uses 2 AA batteries and has incredible battery life. It is the only system I have found that has an approximate 20hr battery life, as opposed to 4-6 hrs with most systems. I recommend rechargeable AA batteries and charger be purchased from most any electronic/department store. A 4 battery system with batteries and charger can generally be found for \$10-15. I then recommend that you simply place the batteries in the charger at the end of each shift when you charge your walkie. Because of the long battery life, you can simply turn the transmitter on at the start of a shift and leave it on for the entire shift. The audio will only record when the unit is activated, but it will prevent you from missing critical audio when something comes up and you had forgotten to turn it on. If needed, it could of course be turned off should you not want audio to record.

The belt pack transmitter can be clip to your belt or carried in a pocket. If you wish to put in a pocket, you can fold the antennae to one side so that a pocket flap will close. You can then clip the microphone to a pocket pf remove the clip on the microphone and place the microphone inside a pocket fold.